Interference-signal-dependent adaptive echo suppression

The invention concerns a method for reducing echo signals
in telecommunications systems for the transmission of
5 wanted acoustic signals, particularly human speech, in
which the presence of echo signals is detected and/or
predicted and the detected and/or predicted echo signals
are subsequently suppressed or reduced.

10 Such a method is known from, for example, DE 42 29 912 A1.

Echo and noise suppression is assuming increasing
importance for speech quality in communications networks,
in which telephone transmissions are often noticeably
15 affected by interference due to line or acoustic echoes and
background noise.

Cordless telephones, particularly mobile telephones, are
becoming increasingly widespread. In order to achieve a
20 reasonable quality of communication with sets of ever
smaller dimensions and, consequently, increasing acoustic
coupling from the loudspeaker to the microphone, these sets
normally comprise devices for compensating acoustic echoes.
The technique of the adaptive filter for echo compensation
25 is described in, for example, DE 44 30 189 A1.

In the case of older mobile telephones or cheaper, new
mobile telephones of simple technical construction,
however, substantial acoustic echoes continue to be
30 produced which enter the PSTN (= Public Switched Telephone
Network), where they seriously interfere with communication
with other fixed or mobile telecommunications users. The

mobile telecommunications operators therefore endeavour to eliminate these echoes in order to recruit new customers with the argument of a sound quality which is better than that of competitors.

5

Since the acoustic echoes are produced, but not completely suppressed, in the cheap mobile telephones, the network operators generally have no option other than to attempt to suppress the echoes in the next switching center. Ordinary

10 adaptive filters are used to model a line echo which, with correct setting of the filter, simulates the actually occurring echoes. The modelled line echo is then subtracted from the telecommunications signal affected by the echo. However, the technique of the adaptive filter

15 cannot be successfully used in the case of mobile telephone echoes because the original speech towards the mobile telephone is speech-coded and the echo in the mobile telephone undergoes further speech coding. For this reason, only newer, non-linear methods such as, for

20 example, "center clippers", controlled attenuators or NLP are suitable for the suppression of mobile telephone acoustic echoes. Adaptive filters are suitable for acoustic echoes of fixed telephones, but are generally relatively expensive.

25

With the introduction of methods of echo and noise reduction, the methods did not initially take account of the severity of interference with speech signals. For example, a spectral subtraction was effected with the

30 greatest possible gain, or the degree of an echo and noise reduction was set to the highest possible values, in order to produce as good an auditory perception as possible with

a reasonable, medium-level signal-to-noise ratio. All of
these methods, however, produce clearly audible
interference in the case of a poor signal-to-noise ratio or
weak wanted signals.

5

Manifestly disadvantageous in the case of the known methods
is the fact that, in the case of relatively loud, clearly
audible noise and simultaneously large reduction of echo
into the background noise due to the echo suppression, the
10   occurrence of transient echo peaks causes "holes" to be
"punched" into the otherwise uniform background noise,
resulting in what is perceived as a disagreeable modulation
of the transmitted telecommunications signal in the speech
pauses.

15

The object of the present invention, by contrast, is to
present a method, having the initially described features,
with which reduction of the echo signals can be effected,
as inexpensively as possible and with simplest means, so as
20   to produce an overall acoustic perception of the
transmitted telecommunications signal which sounds as
comfortable as possible to the human ear.

This object is achieved both simply and effectively,
25   according to the invention, in that the power value of the
noise level N in the currently used telecommunications
channel is continuously measured and/or estimated, and that
the degree of reduction of the echo signals to be currently
effected is set continuously and automatically, in
30   dependence on the current noise level N, according to a
predefined function h(N).

The degree of an echo reduction or echo suppression is thus automatically and simultaneously controlled by the currently occurring power value N of the noise, matched to the current noise value in the telephone channel and

5   corrected in a predetermined, defined manner. The subjective perception of the resultant overall signal can also be adjusted through the selection of the function h(N). The occurrence of "holes" in the background noise due to an excessive echo suppression is effectively avoided

10 by the method according to the invention.

By use of the method according to the invention, the input-side noise signal N is advantageously reduced, by multiplication by the factor h(N), to a value N_A, according

15 to the equation $N_A = N * h(N)$.

A preferred embodiment of the method according to the invention is characterized by the fact that the function h(N) increases as N increases, whereby

20 $h(N << 0\ dB_m) = h_{min} = const.$ and $h(N \approx 0\ dB_m) = h_{max} > h_{min}$.

A particularly favourable psychoacoustic auditory perception of the telecommunications signals is achieved, following implementation of the echo reduction according to

25 the invention, if

-50 dB < h_{min} < -20 dB, preferably -45 dB ≤ h_{min} ≤ -35 dB and

-20 dB < h_{max} < 0 dB, preferably -12 dB ≤ h_{max} ≤ -6 dB.

30 Particularly preferred is a variant of the method according to the invention which is characterized by the fact that the predefined function h(N) is a function k(S/N) which

depends on the signal-to-noise ratio, i.e., the quotient
S/N from the power value of the signal level S of the
wanted signals to be transmitted and the power value of the
noise level N, or that the predefined function $h(N)$ is a
5   function $k'(N/S)$ which depends on the reciprocal N/S of
this quotient, preferably on $N/(N+S)$.

For reasons of simpler, practical realization, a function
of $(S+N)/N$ or of $(S+N)/S$ can also be used. Particularly
10   practical for realization of the method on a digital signal
processor (= DSP) is the use of the function $k'[N/(N+S)]$,
which runs between 0 and 1.

An advantage of the above method variant is that, in the
15   case of large variation of the wanted signal level S in the
telephone channels of a group, the correct setting is
always found for the echo reduction. In the case of the
echo reduction being controlled proportionally in relation
to the reciprocal N/S or $N/(N+S)$, the function k' can be
20   easily implemented on a DSP with fixed computer word
lengths, for example, of 16 bits, through the use of
particularly simple software since, for N/S or $N/(N+S)$, a
number range of preferably $0 < N/S$ or $N/(N+S) < 1$ is
relevant or useful for controlling the noise reduction.
25

During normal person-to-person communication, the amplitude
of the spoken speech is generally adapted automatically to
the acoustic environment. In the case of a speech
communication between distant locations, however, the
30   conversing partners are not located in the same acoustic
environment and are each therefore unaware of the acoustic
situation at the location of the other conversing partner.

A particularly aggravated problem therefore occurs if one of the partners is compelled by their acoustic environment to speak very loudly while the other partner, in a quiet acoustic environment, produces speech signals of low

5 amplitude. Added to this is the problem that an "electronically generated" noise is also produced on a telecommunications channel and is simultaneously transmitted as background to the wanted signal. Furthermore, it is also advantageous to reduce or suppress

10 interference signals such as unwanted background noise (street noise, factory noise, office noise, canteen noise, aircraft noise, etc.). In order to improve auditory comfort in telephoning, it is generally sought to keep noise of all kinds to a minimum.

15

In addition to the recognition and reduction of echo signals according to the invention, noise signals in the telecommunications channel are preferably also suppressed or reduced. An auditorially adapted noise reduction can

20 thus be advantageously combined with an echo reduction, working independently of the noise reduction.

In the case of the known compander method as described in, for example, the initially cited DE 42 29 912 A1, the

25 degree of noise reduction is determined according to a set, predefined transfer function.

The compander, firstly, has the characteristic of transferring speech signals with a determined (pre-set)

30 "normal speech signal level" (sometimes referred to as normal loudness) virtually unchanged from its input to the output.

If, however, the input signal happens to be too loud due, for example, to one speaker being too close to their microphone, a dynamic compressor limits the output level to

5   virtually the same value as in the normal case through linear reduction of the current gain in the compander as the input loudness increases. Due to this characteristic, the speech at the output of the compander system remains at approximately the same loudness - irrespective of the

10   extent of fluctuation of the input loudness.

If, on the other hand, a signal is input to the compander at a level which is less than the normal level, the signal undergoes additional attenuation through reduction of the

15   gain in order that, as far as possible, only attenuated background noise is transmitted. The compander thus comprises two sub-functions, a compressor for speech signal levels which are greater than or equal to a normal level, and an expander for signal levels which are less than the

20   normal level.

Particularly preferred is a variant of the above embodiment of the method according to the invention in which the degree of reduction of the noise level N to be currently

25   effected is set continuously and automatically, in dependence on the current noise level N, according to a predefined function f(N) or g(S/N) or g'(N/S), preferably g'(N/[N+S]). The degree of the noise reduction is thus determined according to the particular situation and used

30   to control a noise suppression. This, by simple means, enables an overall acoustic perception to be produced which

is as comfortable as possible to the human ear and can be adapted to individual requirements according to preference.

A further advantage of this particularly preferred method
5 variant is that, in the case of a group of telephone channels, for example between international switching centers, the noise situation, which can of course vary greatly from one channel to another, can be automatically set and individually optimized in each separate channel.
10

Particularly good results are achieved with this noise reduction method variant if, for $N \ll 0$ dB_m, the functions $f(N)$, $g(S/N)$, $g'(N/S)$ or $g'([N/N+S])$ each begin, respectively, with a constant maximum value f_{max} or g_{max} or
15 $g'_{max} \approx 1$ (corresponding to 0 dB), fall to a minimum value f_{min} or g_{min} or g'_{min} respectively in the range between $N = -15$ dB_m to -10 dB_m, preferably for N or $S/N \approx -12$ dB, and then rise, to $N \approx 0$ dB_m, to a constant value $f_0 > f_{min}$ or $g_0 > g_{min}$ or $g'_0 > g'_{min}$ respectively, wherein f_0, g_0, $g'_0 < 1$
20 (corresponding to 0 dB), preferably $0.35 < f_0$, g_0, $g'_0 < 0.75$ (which corresponds to an interval -12 dB $< f_0$, g_0, $g'_0 < -3$ dB).

Acoustic auditory tests have shown that, for $S/N = 0$ dB,
25 the speech is already so greatly affected by interference that the noise can be reduced only relatively, by a value f_0 or g_0 between -5 and -10 dB, preferably between -6 and -8 dB, in order that the overall acoustic perception is not impaired in respect of naturalness of the speech. In the
30 case of even less favourable values of the signal-to-noise ratio $S/N < 0$ dB, the value f_0 or g_0 can then only be

maintained, since each further noise reduction only impairs the overall perception.

According to these studies, a greater noise reduction can be effected in the case of a medium-level S/N. A minimum is obtained in the range 10 dB to 15 dB. The noise reduction value f_{min} or g_{min} can be settable between −3 dB and −30 dB and, at maximum, should be between −12 dB and −30 dB, preferably approximately −18 dB.

In the case of very good signal-to-noise ratios S/N >40 dB, only a minimal reduction should be set, between 0 and −3 dB, in order maintain as far as possible the naturalness of the transmitted speech. According to ITU-T G. 168 for echo cancellers, a noise at S/N > 40 dB is to be left unchanged, this corresponding to a numerical value f_{max} or $g_{max} = 1$ (corresponding to 0 dB).

The sound and intelligibility of the speech are particularly good if the functions h(N), f(N), k(S/N), g(S/N) or k'(N/S) and g'(N/S) connect together in a continuous manner beyond the three ranges discussed above, rapid changes in N or in S/N being advantageously smoothed through filtering operations.

A relatively simple hardware and/or software realization is achieved in that the said functions h(N), f(N), k(S/N), g(S/N) or k'(N/S) and g'(N/S) are approximated by straight characteristic portions between the three operating points described above (sectional linear approximation).

In the case of a variant of the method according to the invention which is somewhat more complex but which results in a better tonal response, a polynomial function is used for implementation of the continuous functions $h(N)$, $f(N)$, $k(S/N)$, $g(S/N)$ or $k'(N/S)$ and $g'(N/S)$ in the three discussed ranges, resulting in a kind of asymmetric bell-shaped function.

For a satisfactory compromise between complexity and tonal response, defined sections of the above-mentioned functions can be realized by straight characteristic portions and other sections by a polynomial function.

Particularly preferred is a variant of the method according to the invention in which the functions $h(N)$, $f(N)$, $k(S/N)$, $g(S/N)$ or $k'(N/S)$ and $g'(N/S)$ are selected so that the reduction of the noise level N is auditorially adapted according to the psychoacoustic mean values of the human auditory spectrum. In this case, the value for S and/or N is determined not only from the instantaneous power value alone, but also from a weighted spectral course of S or N and an auditorially adapted noise reduction, i.e., a psychoacoustically comfortable-sounding noise reduction, is achieved overall through the function obtained thus. Since there is no measure of an acoustically comfortable-sounding noise reduction which can be easily represented, all quality evaluations are assigned to comprehensive auditory tests which are then evaluated by means of statistical methods optimized for that purpose, in order to obtain an evaluation criterion (in a manner similar to that in the case of speech codes).

A good estimation of noise level requires a good speech
pause detector, since only then is it possible to be
certain that only interfering noise is present in the
speech pause intervals rather than some mixture of noise

5 and traces of speech, as frequently occurs in practice.

In order to achieve an effective noise reduction, the power
value of the signal to be transmitted is preferably reduced
during the speech pauses according to an exponential

10 function. A substantial noise reduction is already
achieved by this means. During the speech intervals,
noises are at least partially masked by the speech itself
and are therefore less noticeable overall. Furthermore, a
reduction of noise during a speech pause imposes

15 appreciably less strain on the hearing by substantially
reducing the deafness effect following exposure to loud
sound. Upon resumption of speech, the ear can react with
greater sensitivity and listen with greater accuracy.

20 Also particularly preferred is a method variant which is
characterized by the fact that, in the speech pause
detector, from the input signal x, a short-time output
signal sam(x) is formed by means of a short-time level
estimator, a medium-time output signal mam(x) is formed by

25 means of a medium-time level estimator and a long-time
output signal lam(x) is formed by means of a long-time
level estimator, that the three output signals sam(x),
mam(x) and lam(x) are set, by means of appropriate gain
coefficients, so that they are of approximately equal

30 magnitude if the input signal x is a pure noise signal, it
being the case that sam(x) < mam(x) < lam(x), that the
three output signals sam(x), mam(x) and lam(x) are

monitored by comparators, and that the presence of a speech
signal is assumed as the input signal x if sam(x) and
mam(x) each become initially greater than lam(x) and the
presence of a speech pause is assumed if sam(x) and/or

5 mam(x) subsequently becomes less than lam(x).

By means of these relatively simple methods of forming
different mean values of the time signal, it is already
possible to effect surprisingly good speech pause detection

10 requiring only a very small amount of computation effort.

A development of this method variant provides for the three
output signals sam(x), mam(x) and lam(x) being applied, for
the purpose of speech pause estimation, to a neural network

15 which has been trained with a plurality of scenarios with
different input signals x. A neural network can
advantageously map linear and non-linear relationships
between a large quantity of input parameters and the
desired output values. A prerequisite for this is that the

20 neural network has been trained once with a sufficient
quantity of input values and associated output values. For
this reason, neural networks are particularly suitable for
the task of speech pause detection in the presence of
different interfering noises.

25

It is expedient to separate noise reduction control from
echo reduction control, since noises and echoes occur
independently of one another and generally also have
completely different physical causes. However, it is

30 possible to state mathematically a general reduction
function R, which describes a reduction of signal levels
for both noises and echoes:

$$R(S, N, ES, \tau_E, ERL, thrs) \sim g(S/N) \cdot d(N, ES, \tau_E, ERL, thrs),$$

wherein $g(S/N)$ denotes the noise reduction described above
and $d(...)$ denotes the noise-dependent echo reduction to be
applied independently and additionally if the estimated
echo signal exceeds the predefined threshold value thrs.

Particularly advantageous is a method variant in which an
artificial noise signal is also added to the wanted signal
during an echo reduction period. When a noise level is
constant, a noise reduction is likewise constant. An
additional echo reduction occurring suddenly in the rhythm
of the speech also means a noise reduction (at least in the
short time interval) in the speech rhythm. This results in
a pulsed background noise, which does not sound natural.
It is therefore advantageous to add a synthetic noise of an
appropriate noise generator, of the order of magnitude of
the normal background noise, to the processed signal in the
instants of an additional echo reduction. The purpose of
this is to relay a background noise which, for the
listener, is as uniform as possible. The "holes" in the
background noise due to the echo reduction, discussed
above, can thus be at least partially "filled in".

The noise generator can be designed so that the artificial
noise signal comprises a signal sequence which is perceived
psychoacoustically as an acoustically comfortable noise (=
comfort noise).

Instead of a synthetic background noise, however, it is
also possible to insert into the echo time intervals, at

matched intensity, a portion of a previously recorded real
background noise. The added noise is then virtually
indistinguishable from the previous noise and will
therefore cause scarcely any acoustically interfering
5   variations for the listener. Only at the switching centers
can discrepancies occur very briefly between the original
noise and the added noise.

If correctly matched to one another, the addition of noise
10   for the purpose acoustic masking of effects and the
measures for separate processing of noise and echoes will
result in a particularly intelligible and comfortable
speech perception, even in the case of a "difficult"
environment (echoes plus noise).
15

Also included within the scope of the present invention is
a server unit for supporting the method according to the
invention described above and a computer program for
executing the method. The method can be realized both as a
20   hardware circuit and in the form of a computer program.
Nowadays, software programming for powerful DSPs is
preferred, since new knowledge and additional functions can
be more easily implemented by altering the software on an
existing hardware base. However, methods can also be
25   implemented as hardware modules, for example in
telecommunications terminal devices or telephone equipment.

Further advantages of the invention are disclosed by the
description and the drawing. The features stated above and
30   those to be stated below can also each be applied,
according to the invention, either singly or multiply in
any combinations. The embodiments represented and

described are not to be understood as a definitive list but are rather of an exemplary character for the purpose of describing the invention.

5   The invention is represented in the drawing and is described more fully with reference to embodiment examples.

The figure shows an actual embodiment example for the functions k'[N/(N+S)] and g'[N/(N+S)].

10

Example: calculation of a pair g'(.) and k'(.)

i) The desired function g'(.)=NLA(.) for noise reduction can be described by, for example, combining straight-line
15   portions with portions of a polynomial function; in the simplest case, for example, by means of a polynomial of nth degree (2<n<5) and a straight line. The noise reduction factor NLA (as gain value) is thus obtained according to equation (1):

20

$$(1) \quad g'(.) \;=\; \begin{cases} if\ (x = N/(N+S) \le -40\,dB & then\ g'(.) = 1 \\ if\ (-40\,dB < x = N/(N+S) \le -12\,dB) & then \\ \quad\ g'(.) = a_n\,x^n + a_{n-1}\,x^{n-1} + .. + a_1\,x + a_0 & (polynomial\ portion) \\ if\ (-12\,dB < x = N/(N+S) \le 0\,dB & then \\ \quad\ g'(.) = m\,x + c & (straight\ line) \end{cases}$$

The coefficients {a_n, a_{n-1}, … a_1, a_0} of the polynomial and the coefficients {m, c} of the straight line are calculated
25   so that they coincide at the desired point A.

ii) The associated function of the echo damping ERLE[N/(N+S)] = k'(.) can also be described by, for

example, combining straight-line portions with portions of a polynomial function. In this example, according to equation (2), it is preferably composed of two straight-line portions which are selected so that they are suitably

5   matched to the particular situation.

$$
(2) \quad k'(.) = \begin{cases} \textit{if } (x = N/(N+S) \leq \textit{-12 dB} & \textit{then} \\ \quad k'(.) = x \left(\dfrac{g'(A) \bullet \varDelta - h_{min}}{0.25} \right) + h_{min} & \textit{(straight line portion 1)} \\ \textit{if } (-12 \textit{ dB} < x = N/(N+S) \leq 0 \textit{ dB}) & \textit{then} \\ \quad k'(.) = g'(x) \quad \varDelta & \textit{(straight line portion 2)} \end{cases}
$$

In this equation, g'(A) denotes the numerical value (real)

10   of g'(.) at the point "A" and Δ denotes a factor by which this value is reduced so that the function k'(.) runs parallel to the function g'(.), at a distance of Δ.

According to Rec. ITU-T G.168, a noise to a level of -40 dB

15   at the input of an echo canceller is to be unchanged, i.e., is to be transmitted at the same level. This functionality is fulfilled by the first condition for g'(.) according to equation (1).

20   It is particularly advantageous if, in the position of the point A, the magnitude of h_{min} and the distance Δ between the two functions g' and k' can be freely selected and set according to the actual requirements in the particular case. In displacement of the point A, the function k'

25   should adjust automatically to the changed function g'.